



## Robust housing solution for cabinet mounting



(Figure similar)



Figure	Type	Inputs digital	Outputs digital	Input voltage (sensor supply) <sup>(1)</sup>	Output voltage (actuator supply) <sup>(2)</sup>	ASi connection <sup>(3)</sup>	ASi address <sup>(4)</sup>	Article No.
	stainless Steel, IP20, depth: 45 mm	4	3 x relay	out of ASi	–	clamps	1 AB slave	<b>BW1808</b>
	stainless Steel, IP20, depth: 45 mm	4	4 x relay	out of ASi	–	clamps	1 single slave	<b>BW1926</b>
	stainless Steel, IP20, depth: 45 mm	4	4 x electronic	out of AUX	out of AUX	clamps	1 AB slave	<b>BW1907</b>
	stainless Steel, IP20, depth: 45 mm	4	4 x electronic	out of AUX	out of AUX	clamps	1 single slave	<b>BWU2565</b>
	stainless Steel, IP20, depth: 45 mm	8	–	out of AUX	–	clamps	2 AB slaves	<b>BWU2077</b>
	stainless Steel, IP20, depth: 45 mm	–	8 x electronic	–	out of AUX	clamps	2 AB slaves	<b>BW2078</b>
	stainless Steel, IP20, depth: 90 mm	4	4 x relay	out of ASi	–	clamps	1 single slave	<b>BW2555</b>
	stainless Steel, IP20, depth: 90 mm	8	–	out of AUX	–	clamps	2 AB slaves	<b>BW2556</b>


**Replacement, ASi version 2: Single Slaves (digital), work even with the first ASi Masters.**

- (1) **Input voltage (sensor supply):** inputs are supplied by ASi or by AUX (auxiliary 24 V power). If supplied by ASi, inputs shall not be connected to earth or to external potential.
- (2) **Output voltage (actuator supply):** Electronic outputs are supplied by ASi or by AUX (auxiliary 24 V power). If supplied by ASi, outputs shall not be connected to earth or to external potential. For relay outputs the relay contacts are initiated from ASi. The load circuit is powered externally as specified in the data sheet.
- (3) **ASi connection:** the connection to ASi as well to AUX (auxiliary 24 V power) is made via yellow resp. black ASi profile cable with piercing technology or via M12 socket (in IP20 via clamps).
- (4) **ASi address:** 1 AB Slave (max. 62 AB Slaves/ASi network), 2 AB Slaves (max. 31 modules with 2 AB Slaves), Single Slaves (max. 31 Single Slaves/ASi network), mixed use allowed.  
For modules with two slaves the second slave is turned off as long as the first slave is addressed to address "0".  
Upon request, slaves are available with specific ASi Slave profiles.

Article no.	BW1808		BW1926		BW2555	
<b>General data</b>						
Device type	input / output					
<b>Connection</b>						
ASi / AUX connection	spring type terminals					
Periphery connection	spring type terminals					
Length of connector cable	I: max. 1,5 m O: unlimited <sup>(1)</sup>					
<b>ASi</b>						
Profile	S-7.A.E, ID1= 7 (default)		S-7.F.E, ID1= F (default)			
ASi address	1 AB slave		1 single slave			
Required Master profile	≥M3		≥M0			
Since ASi specification	2.1		2			
Operating voltage	30 V (26 ... 31,6 V)					
Max. current consumption	200 mA					
Max. current consumption without sensor/ actuator supply	<30 mA					
<b>AUX</b>						
Voltage	-					
Max. current consumption	-					
<b>Input</b>						
Number	4					
Power supply	out of ASi					
Power supply of attached sensors	max. 100 mA					
Input level	inputs 24 V <sub>DC</sub> < 0,8 mA (low) > 5 mA (high)					
<b>Output</b>						
Number	up to +40 °	3 x relays, change over, 230 V; 10 A <sup>(2)</sup> (AC1)		4 x relays, change over, 230 V; 10 A <sup>(2)</sup> (AC1)		
	at +70 °C	3 x relays, change over, 230 V; 4 A <sup>(2)</sup> (AC1)		4 x relays, change over, 230 V; 4 A <sup>(2)</sup> (AC1)		
Relay control	out of ASi					
Max. output current	-					
<b>Display</b>						
LED PWR (green)	ASi voltage o.k.					
LED AUX (green)	-					
LED FLT/FAULT (red)	communication error					
LEDs I1 ... In (yellow)	state of inputs I1 ... I4					
LEDs O1 ... On (yellow)	state of outputs O1 ... O3		state of outputs O1 ... O4			
<b>Environment</b>						
Applied standards	EN 61000-6-2 EN 61000-6-3 EN 60529					
Passive safety (up to PLe/SIL 3)	yes <sup>(3)</sup>					
UL certified	yes					
Operating altitude	max. 2000 m					
Ambient temperature	-25 °C ... +45 °C (up to max. +70 °C) <sup>(4)</sup>					
Storage temperature	-25 °C ... +70 °C					
Housing	stainless steel, for DIN rail mounting					
Protection category	IP20					
Weight	330 g			440 g		
Dimensions (W / H / D) in mm	50 / 120 / 45			50 / 120 / 90		

(1) Loop resistance:  $\leq 150 \Omega$ .

(2)



It is possible to connect multiple relay modules in parallel.

(3) BWU4230 from Ident. No. 18442; Exclusion of errors for the connection of the two ASi and AUX potentials can be assumed in the module. Passive safety for the application can only be achieved if this is ensured for all components used.


(4) Maximum ambient operating temperature +45 °C according UL certificate for the use in the USA and Canada.


Article no.	BWU2565		BW1907
<b>General data</b>			
Device type	input/output		
<b>Connection</b>			
ASi / AUX Connection	spring type terminals		
Periphery connection	sprint type terminals		
Length of connector cable	I/O: max. 1,5 m <sup>(1)</sup>		
<b>UL-specifications (UL61010-1 and UL61010-2-201)</b>			
External protection	An isolated source with a secondary open circuit voltage of $\leq 30 V_{DC}$ with a 3 A maximum over current protection. Over current protection is not required when a Class 2 source is employed.		
<b>ASi</b>			
Profile	S-7. F. E, ID1=7 (fixed)	S-7.A.7, ID1= 7 (fixed)	
Address	1 Single Slave	1 AB Slave	
Required Master profile	$\geq M0$	$\geq M4$	
Since ASi specification	2	3	
Operating voltage	30 V (18 ... 31,6 V)		
Max. current consumption	60 mA		
Max. current consumption without sensor/ actuator supply	<30 mA		
<b>AUX</b>			
Voltage	24 V (18 ... 30 V)		
Max. current consumption	AUX-I: 1,2 A permanent operating; 4 A max.	AUX-I: 1,2 A permanent operation; 4 A max.	
	AUX-O: 1,2 A permanent operation; 4 A max.	AUX-O: 2 A permanent operation; 4 A max.	
	in total: 8 A max.	in total: 8 A max.	
<b>Input</b>			
Number	4		
Power supply	out of AUX		
power supply of attached sensors	up to +40 °C	1,2 A permanent operation <sup>(2)</sup>	
	at +55 °C	0,9 A permanent operation <sup>(2)</sup>	
	at +70 °C	0,6 A permanent operation <sup>(2)</sup>	
Switching threshold	inputs 24 $V_{DC}$ < 0,8 mA (low) > 5 mA (high)		

Article no.		BWU2565	BW1907
<b>Output</b>			
Number		4 x electronic	
Power supply		out of AUX	
Max. output current	up to +40 °C	0,5 A per output, $\Sigma$ (Out) 1,2 A <sup>(3)</sup>	
	at +55 °C	0,5 A per output, $\Sigma$ (Out) 0,9 A <sup>(3)</sup>	
	at +70 °C	0,5 A per output, $\Sigma$ (Out) 0,6 A <sup>(3)</sup>	
<b>Display</b>			
LED PWR (green)		on: ASi voltage o.k	
LED AUX (green)		AUX-I: AUX voltage for inputs o.k., AUX-O: AUX voltage for outputs o.k.	
LED FLT/FAULT (red)		on: communication error flashing: AUX I voltage missing or overload	
LEDs I1 ... In (yellow)		state of input I1 ... I4	
LEDs O1 ... On (yellow)		state of outputs O1 ... O4	
<b>Environment</b>			
Applied standards		EN 61000-6-2 EN 61000-6-3 EN 60529	
Passive safety (up to PLe/SIL 3)		no <sup>(4)</sup>	
UL certified		no	
Operating altitude		max. 2000 m	
Ambient temperature		-25 °C ... +70 °C	
Storage temperature		-40 °C ... +70 °C	
Housing		stainless steel, for DIN rail mounting	
Protection category		IP20	
Weight		330 g	
Dimensions (W / H / D) in mm		50 / 120 / 45	

(1) Loop resistance:  $\leq 150 \Omega$ .

(2)






(4) Exclusion of errors for the connection of the two ASi and AUX potentials cannot be assumed in the module. It is not possible to achieve passive safety for the application with this module.

Article no.	BW2078	BWU2077	BW2556
<b>General data</b>			
Device type	output		input
<b>Connection</b>			
ASi / AUX Connection		spring type terminals	
Periphery connection		spring type terminals	
Length of connector cable	O: max. 1,5 m <sup>(1)</sup>		I: max. 1,5 m <sup>(1)</sup>
<b>UL-specifications (UL61010-1 and UL61010-2-201)</b>			
External protection	An isolated source with a secondary open circuit voltage of ≤30 V <sub>DC</sub> with a 3 A maximum over current protection. Over current protection is not required when a Class 2 source is employed.		
<b>ASi</b>			
Profile	S-7.A.7, ID1= 7 (fixed)		2 x S-0.A.E, ID1= 7 (fixed)
Address		2 AB Slaves	
Required Master profile	≥M4		≥M3
Since ASi specification	3		2.1
Operating voltage	30 V (26 ... 31,6 V)		30 V (18 ... 31,6 V)
Max. current consumption	80 mA		100 mA
Max. current consumption without sensor/ actuator supply	<30 mA		
<b>AUX</b>			
Voltage	24 V (18 ... 30 V)		
Max. current consumption	AUX1: 2 A permanent operation; 4 A max. AUX2: 2 A permanent operation; 4 A max. in total: 8 A max.		AUX: 1,2 A permanent operation; 4 A max.
<b>Input</b>			
Number	–		8
Power supply	–		out of AUX
power supply of attached sensors	up to +40 °C	–	1,2 A permanent operation <sup>(4)</sup>
	at +55 °C		0,9 A permanent operation <sup>(3)</sup>
	at +60 °C		0,8 A permanent operation <sup>(3)</sup>
Switching threshold	–		inputs 24 V <sub>DC</sub> < 0,8 mA (low) > 5 mA (high)


Article no.		BW2078	BWU2077	BW2556
<b>Output</b>				
Number		8 x electronic		–
Power supply		out of AUX		–
Max. output current	up to +40 °C	0,5 A per output, $\Sigma$ (O1 ... O4) 1,2 A + $\Sigma$ (O5 ... O8) 1,2 A <sup>(2)</sup>		–
	at +55 °C	0,5 A per output, $\Sigma$ (O1 ... O4) 0,9 A + $\Sigma$ (O5 ... O8) 0,9 A <sup>(2)</sup>		
	at +60 °C	0,5 A per output, $\Sigma$ (O1 ... O4) 0,6 A + $\Sigma$ (O5 ... O8) 0,8 A <sup>(2)</sup>		
<b>Display</b>				
LED PWR (green)			on: ASi voltage o.k. flashing: address 0	
LED AUX (green)		AUX 1, AUX 2: AUX voltage o.k.		AUX voltage o.k.
LED FLT/FAULT (red)		communication error		on: communication error flashing: AUX voltage missing or overload
LEDs I1 ... I8 (yellow)		–		state of inputs I1 ... I8
LEDs O1 ... O8 (yellow)		state of outputs O1 ... O8		–
<b>Environment</b>				
Applied standards		EN 61000-6-2 EN 61000-6-3 EN 60529		EN 61131-2 EN 61000-6-2 EN 61000-6-3 EN 60529
Passive safety (up to PLe/SIL 3)				no <sup>(3)</sup>
UL certified				no
Operating altitude				max. 2000 m
Ambient temperature				-25 °C ... +60 °C
Storage temperature				-40 °C ... +70 °C
Housing				stainless steel, for DIN rail mounting
Protection category				IP20
Weight			330 g	440 g
Dimensions (W / H / D) in mm			50 / 120 / 45	50 / 120 / 90

(1) Loop resistance:  $\leq 150 \Omega$ .



(3) Exclusion of errors for the connection of the two ASi and AUX potentials cannot be assumed in the module. It is not possible to achieve passive safety for the application with this module.

(4)



UL-specifications (UL61010)	
<b>BWU2077, BWU2565</b>	
External protection	An isolated source with a secondary open circuit voltage of $\leq 30 V_{DC}$ with a 3 A maximum over current protection. Over current protection is not required when a Class 2 source is employed.
In general	UL mark does not provide UL certification for any functional safety rating or aspects of the above devices.

Programming	Bit setting			
	D3	D2	D1	D0
	input			
<b>BW1808 / BW1907 / BW1926 / BW2555 / BWU2565</b>	I4	I3	I2	I1
<b>BWU2077 / BW2556</b>	slave 1: I4	slave 1: I3	slave 1: I2	slave 1: I1
	slave 2: I8	slave 2: I7	slave 2: I6	slave 2: I5
	output			
<b>BW1808</b>	–	O3	O2	O1
<b>BW1907 / BW1926 / BW2555 / BWU2565</b>	O4	O3	O2	O1
<b>BW2078</b>	slave 1: A4	slave 1: A3	slave 1: A2	slave 1: A1
	slave 2: A8	slave 2: A7	slave 2: A6	slave 2: A5
	parameter bit			
	P3	P2	P1	P0
<b>BW1907 / BWU2565</b>	not used	0= On / 1= Off (synchronous I/O mode)	0= On / 1= Off (data input filter 128 $\mu$ s)	0= Off / 1= On ( Watchdog)
<b>BW1808 / BW1926 / BWU2077 / BW2078 / BW2555 / BW2556</b>	not used			

Connections:																													
<b>BW1808 / BW1926 / BW2555</b>																													
<table border="1"> <tr> <td>ASi+</td> <td>ASi-</td> </tr> <tr> <td>+24V I1</td> <td></td> </tr> <tr> <td>+24V I2</td> <td></td> </tr> <tr> <td>0V 0V</td> <td></td> </tr> <tr> <td>+24V I3</td> <td></td> </tr> <tr> <td>+24V I4</td> <td></td> </tr> <tr> <td>ASi+</td> <td>ASi-</td> </tr> </table>	ASi+	ASi-	+24V I1		+24V I2		0V 0V		+24V I3		+24V I4		ASi+	ASi-	<table border="1"> <tr> <td>PE</td> <td>PE</td> </tr> <tr> <td>K4CM</td> <td>K4NO</td> </tr> <tr> <td>K4NC</td> <td>K3NC</td> </tr> <tr> <td>K3CM</td> <td>K3NO</td> </tr> <tr> <td>K2CM</td> <td>K2NO</td> </tr> <tr> <td>K2NC</td> <td>K1NC</td> </tr> <tr> <td>K1CM</td> <td>K1NO</td> </tr> </table>	PE	PE	K4CM	K4NO	K4NC	K3NC	K3CM	K3NO	K2CM	K2NO	K2NC	K1NC	K1CM	K1NO
ASi+	ASi-																												
+24V I1																													
+24V I2																													
0V 0V																													
+24V I3																													
+24V I4																													
ASi+	ASi-																												
PE	PE																												
K4CM	K4NO																												
K4NC	K3NC																												
K3CM	K3NO																												
K2CM	K2NO																												
K2NC	K1NC																												
K1CM	K1NO																												
<p>● ADDR</p> <p>● PWR</p> <p>● FLT</p> <p>● I1</p> <p>● I2</p> <p>● I3</p> <p>● I4</p> <p>● O1</p> <p>● O2</p> <p>● O3</p> <p>● O4</p>	<table border="1"> <tr> <td>ASi +, ASi -</td> <td>ASi connection</td> </tr> <tr> <td>+24 V, 0 V</td> <td>Sensor supply, generated out of ASi</td> </tr> <tr> <td>PE</td> <td>Protective ground</td> </tr> <tr> <td>I1 ... I4</td> <td>24V inputs</td> </tr> <tr> <td>K1CM ... K4CM</td> <td>Relay common</td> </tr> <tr> <td>K1NO ... K4NO</td> <td>Relay normally open</td> </tr> <tr> <td>K1NC ... K4NC</td> <td>Relay normally closed</td> </tr> </table>	ASi +, ASi -	ASi connection	+24 V, 0 V	Sensor supply, generated out of ASi	PE	Protective ground	I1 ... I4	24V inputs	K1CM ... K4CM	Relay common	K1NO ... K4NO	Relay normally open	K1NC ... K4NC	Relay normally closed														
ASi +, ASi -	ASi connection																												
+24 V, 0 V	Sensor supply, generated out of ASi																												
PE	Protective ground																												
I1 ... I4	24V inputs																												
K1CM ... K4CM	Relay common																												
K1NO ... K4NO	Relay normally open																												
K1NC ... K4NC	Relay normally closed																												
<b>Notice: In article no.: BW1808 the output O4 is not assigned; K4 is not used!</b>																													

Connections:																																	
BW1907 / BWU2565																																	
<table border="1"> <tr> <td>ASi+</td> <td>ASi-</td> </tr> <tr> <td>+24V I1</td> <td></td> </tr> <tr> <td>+24V I2</td> <td></td> </tr> <tr> <td>0V I</td> <td>0V I</td> </tr> <tr> <td>+24V I3</td> <td></td> </tr> <tr> <td>+24V I4</td> <td></td> </tr> <tr> <td>ASi+</td> <td>ASi-</td> </tr> </table>		ASi+	ASi-	+24V I1		+24V I2		0V I	0V I	+24V I3		+24V I4		ASi+	ASi-	<table border="1"> <tr> <td colspan="2">ADDR</td> </tr> <tr> <td>● PWR</td> <td>● AUX-I</td> </tr> <tr> <td>● FLT</td> <td>● AUX-O</td> </tr> <tr> <td>● I1</td> <td>● O1</td> </tr> <tr> <td>● I2</td> <td>● O2</td> </tr> <tr> <td>● I3</td> <td>● O3</td> </tr> <tr> <td>● I4</td> <td>● O4</td> </tr> </table>		ADDR		● PWR	● AUX-I	● FLT	● AUX-O	● I1	● O1	● I2	● O2	● I3	● O3	● I4	● O4		
ASi+	ASi-																																
+24V I1																																	
+24V I2																																	
0V I	0V I																																
+24V I3																																	
+24V I4																																	
ASi+	ASi-																																
ADDR																																	
● PWR	● AUX-I																																
● FLT	● AUX-O																																
● I1	● O1																																
● I2	● O2																																
● I3	● O3																																
● I4	● O4																																
<table border="1"> <tr> <td>+24V I ext.in</td> <td>0V I ext.in</td> </tr> <tr> <td>nc</td> <td>nc</td> </tr> <tr> <td>+24V O ext.in</td> <td>0V O ext.in</td> </tr> <tr> <td>O1</td> <td>0V O</td> </tr> <tr> <td>O2</td> <td>0V O</td> </tr> <tr> <td>O3</td> <td>0V O</td> </tr> <tr> <td>O4</td> <td>0V O</td> </tr> </table>		+24V I ext.in	0V I ext.in	nc	nc	+24V O ext.in	0V O ext.in	O1	0V O	O2	0V O	O3	0V O	O4	0V O	<table border="1"> <tr> <td>ASi +, ASi -</td> <td>Connection to the ASi bus</td> </tr> <tr> <td>+24 V I ext.in, 0 V I ext.in</td> <td>Supply inputs for inputs</td> </tr> <tr> <td>+24 V O ext.in, 0 V O ext.in</td> <td>Supply inputs for outputs</td> </tr> <tr> <td>+24 V I, 0 V I</td> <td>Sensor supply</td> </tr> <tr> <td>0 V O</td> <td>Supply outputs GND for outputs</td> </tr> <tr> <td>I1 ... I4</td> <td>Inputs</td> </tr> <tr> <td>O1 ... O4</td> <td>Outputs</td> </tr> </table>		ASi +, ASi -	Connection to the ASi bus	+24 V I ext.in, 0 V I ext.in	Supply inputs for inputs	+24 V O ext.in, 0 V O ext.in	Supply inputs for outputs	+24 V I, 0 V I	Sensor supply	0 V O	Supply outputs GND for outputs	I1 ... I4	Inputs	O1 ... O4	Outputs		
+24V I ext.in	0V I ext.in																																
nc	nc																																
+24V O ext.in	0V O ext.in																																
O1	0V O																																
O2	0V O																																
O3	0V O																																
O4	0V O																																
ASi +, ASi -	Connection to the ASi bus																																
+24 V I ext.in, 0 V I ext.in	Supply inputs for inputs																																
+24 V O ext.in, 0 V O ext.in	Supply inputs for outputs																																
+24 V I, 0 V I	Sensor supply																																
0 V O	Supply outputs GND for outputs																																
I1 ... I4	Inputs																																
O1 ... O4	Outputs																																
BWU2077 / BW2556																																	
<table border="1"> <tr> <td>ASi+</td> <td>ASi-</td> </tr> <tr> <td>+24V I1</td> <td></td> </tr> <tr> <td>0V O</td> <td>0V O</td> </tr> <tr> <td>+24V I2</td> <td></td> </tr> <tr> <td>+24V I3</td> <td></td> </tr> <tr> <td>0V O</td> <td>0V O</td> </tr> <tr> <td>+24V I4</td> <td></td> </tr> </table>		ASi+	ASi-	+24V I1		0V O	0V O	+24V I2		+24V I3		0V O	0V O	+24V I4		<table border="1"> <tr> <td colspan="2">ADDR 1</td> </tr> <tr> <td colspan="2">● ADDR 2</td> </tr> <tr> <td>● PWR</td> <td>● AUX</td> </tr> <tr> <td>● FLT</td> <td>● I5</td> </tr> <tr> <td>● I1</td> <td>● I6</td> </tr> <tr> <td>● I2</td> <td>● I7</td> </tr> <tr> <td>● I3</td> <td>● I8</td> </tr> <tr> <td>● I4</td> <td>● I8</td> </tr> </table>		ADDR 1		● ADDR 2		● PWR	● AUX	● FLT	● I5	● I1	● I6	● I2	● I7	● I3	● I8	● I4	● I8
ASi+	ASi-																																
+24V I1																																	
0V O	0V O																																
+24V I2																																	
+24V I3																																	
0V O	0V O																																
+24V I4																																	
ADDR 1																																	
● ADDR 2																																	
● PWR	● AUX																																
● FLT	● I5																																
● I1	● I6																																
● I2	● I7																																
● I3	● I8																																
● I4	● I8																																
<table border="1"> <tr> <td>+24V ext.in</td> <td>0V ext.in</td> </tr> <tr> <td>I5</td> <td>+24V</td> </tr> <tr> <td>0V</td> <td>0V</td> </tr> <tr> <td>I6</td> <td>+24V</td> </tr> <tr> <td>I7</td> <td>+24V</td> </tr> <tr> <td>0V</td> <td>0V</td> </tr> <tr> <td>I8</td> <td>+24V</td> </tr> </table>		+24V ext.in	0V ext.in	I5	+24V	0V	0V	I6	+24V	I7	+24V	0V	0V	I8	+24V	<table border="1"> <tr> <td>ASi +, ASi -</td> <td>Connection to the ASi bus</td> </tr> <tr> <td>+24 V ext.in, 0 V ext.in</td> <td>Supply inputs for inputs</td> </tr> <tr> <td>+24 V, 0 V</td> <td>Sensor supply</td> </tr> <tr> <td>I1 ... I8</td> <td>Inputs</td> </tr> </table>		ASi +, ASi -	Connection to the ASi bus	+24 V ext.in, 0 V ext.in	Supply inputs for inputs	+24 V, 0 V	Sensor supply	I1 ... I8	Inputs								
+24V ext.in	0V ext.in																																
I5	+24V																																
0V	0V																																
I6	+24V																																
I7	+24V																																
0V	0V																																
I8	+24V																																
ASi +, ASi -	Connection to the ASi bus																																
+24 V ext.in, 0 V ext.in	Supply inputs for inputs																																
+24 V, 0 V	Sensor supply																																
I1 ... I8	Inputs																																
BW2078																																	
<table border="1"> <tr> <td>ASi+</td> <td>ASi-</td> </tr> <tr> <td>0V 1 ext.in</td> <td>+24 V 1 ext.in</td> </tr> <tr> <td>0V 1</td> <td>O 1</td> </tr> <tr> <td>0V 1</td> <td>O 2</td> </tr> <tr> <td>0V 1</td> <td>O 3</td> </tr> <tr> <td>0V 1</td> <td>O 4</td> </tr> <tr> <td>ASi+</td> <td>ASi-</td> </tr> </table>		ASi+	ASi-	0V 1 ext.in	+24 V 1 ext.in	0V 1	O 1	0V 1	O 2	0V 1	O 3	0V 1	O 4	ASi+	ASi-	<table border="1"> <tr> <td colspan="2">ADDR 1</td> </tr> <tr> <td colspan="2">● ADDR 2</td> </tr> <tr> <td>● PWR</td> <td>● AUX 1</td> </tr> <tr> <td>● FLT</td> <td>● AUX 2</td> </tr> <tr> <td>● O1</td> <td>● O5</td> </tr> <tr> <td>● O2</td> <td>● O6</td> </tr> <tr> <td>● O3</td> <td>● O7</td> </tr> <tr> <td>● O4</td> <td>● O8</td> </tr> </table>		ADDR 1		● ADDR 2		● PWR	● AUX 1	● FLT	● AUX 2	● O1	● O5	● O2	● O6	● O3	● O7	● O4	● O8
ASi+	ASi-																																
0V 1 ext.in	+24 V 1 ext.in																																
0V 1	O 1																																
0V 1	O 2																																
0V 1	O 3																																
0V 1	O 4																																
ASi+	ASi-																																
ADDR 1																																	
● ADDR 2																																	
● PWR	● AUX 1																																
● FLT	● AUX 2																																
● O1	● O5																																
● O2	● O6																																
● O3	● O7																																
● O4	● O8																																
<table border="1"> <tr> <td>+24V 1 ext.in</td> <td>0V 1 ext.in</td> </tr> <tr> <td>+24V 2 ext.in</td> <td>0V 2 ext.in</td> </tr> <tr> <td>+24V 2 ext.in</td> <td>0V 2 ext.in</td> </tr> <tr> <td>O 5</td> <td>0V 2</td> </tr> <tr> <td>O 6</td> <td>0V 2</td> </tr> <tr> <td>O 7</td> <td>0V 2</td> </tr> <tr> <td>O 8</td> <td>0V 2</td> </tr> </table>		+24V 1 ext.in	0V 1 ext.in	+24V 2 ext.in	0V 2 ext.in	+24V 2 ext.in	0V 2 ext.in	O 5	0V 2	O 6	0V 2	O 7	0V 2	O 8	0V 2	<table border="1"> <tr> <td>ASi +, ASi -</td> <td>Connection to the ASi bus</td> </tr> <tr> <td>+24 V1 ext.in, 0 V1 ext.in</td> <td>Supply inputs for outputs outputs O1 ... O4</td> </tr> <tr> <td>+24 V2 ext.in, 0 V2 ext.in</td> <td>Supply inputs for outputs outputs O5 ... O8</td> </tr> <tr> <td>0 V1</td> <td>Reference potential for outputs O1 ... O4</td> </tr> <tr> <td>0 V2</td> <td>Reference potential for outputs O5 ... O8</td> </tr> <tr> <td>O1 ... O8</td> <td>Outputs</td> </tr> </table>		ASi +, ASi -	Connection to the ASi bus	+24 V1 ext.in, 0 V1 ext.in	Supply inputs for outputs outputs O1 ... O4	+24 V2 ext.in, 0 V2 ext.in	Supply inputs for outputs outputs O5 ... O8	0 V1	Reference potential for outputs O1 ... O4	0 V2	Reference potential for outputs O5 ... O8	O1 ... O8	Outputs				
+24V 1 ext.in	0V 1 ext.in																																
+24V 2 ext.in	0V 2 ext.in																																
+24V 2 ext.in	0V 2 ext.in																																
O 5	0V 2																																
O 6	0V 2																																
O 7	0V 2																																
O 8	0V 2																																
ASi +, ASi -	Connection to the ASi bus																																
+24 V1 ext.in, 0 V1 ext.in	Supply inputs for outputs outputs O1 ... O4																																
+24 V2 ext.in, 0 V2 ext.in	Supply inputs for outputs outputs O5 ... O8																																
0 V1	Reference potential for outputs O1 ... O4																																
0 V2	Reference potential for outputs O5 ... O8																																
O1 ... O8	Outputs																																